



**RADIO FREQUENCY  
INDUSTRIES (PTY.) LTD.**

*"Simply The Best"*

CK No : 2005/006095/07    Phone : +27(0)11 869 9285  
VAT No : 4470219918        Fax : +27(0)86 509 2874  
rf-sales@rfind.co.za        Cell : +27(0) 82 765 3007

24 Hendrik Potgieter Street,    P.O. Box 1500  
Corner 5th Avenue                ALBERTON  
ALBERTON NORTH, 1450        1450

## MA-DUCK-400 HELICAL MOBILE ANTENNA (365 - 500 MHz.)



The MA-DUC-400 helical mobile antenna is designed to cover the full frequency range from 365MHz.to 500MHz. by cutting the antenna to length for the required frequency.

The materials used are of the best quality available and will ensure a long life of the product in the harsh African climate.

Plating on the base and adaptors is of the best quality.

The cable is sealed at the base for moisture penetration.

All mobiles are delivered with a cutting chart to provide an **indication** of the whip length at required frequencies.

All models come with 5 Meters of RG58U coaxial cable as standard.

The Mobile Duck range of antennas are guaranteed to fit on 5mm thick material and is therefore the obvious choice for off-road vehicles where the antenna needs to be mounted on roll bars or roof carriers where the material is thicker than normal vehicle body panels.

The Mobile Duck antennas provide very low VSWR readings and therefore gives very good all round performance and best value for money. All the antennas in the Scorpion range fits on the attractive magnetic mounts supplied by RF Industries.

### SPECIFICATIONS:

	<u>MA-DUCK-400</u>
Power :	100Wwatts
Frequency Range :	365-500 MHz.
Impedance :	50 Ohm
Gain:	Unity
Packed Size :	185X60X45 mm
Cable Length:	5 Met. RG58
Mounting :	0 TO 360 DEG.

### NOTES WHEN DETERMINING LENGTH OF MOBILE ANTENNAS:

When determining the lengths of mobile antennas please take in to consideration the size of the ground plane. The rule is the smaller the ground plane the longer whip must be. When working with small ground planes the VSWR may be higher than the specifications indicated on this document. Positioning of the antenna plays a crucial role and again the length and specifications may change depending on where the antenna is mounted. When magnetic mount bases are used, add 10 to 15% to the indicated length to obtain acceptable VSWR.

Manufacturers of : Two-Way Radio Antennas, Duplexers, Filters, Combiners, Splitters, Lightning protectors & other RF Products.  
Sales and Distribution of: Two-Way Radios, Repeater Systems, Power Meters, Microphones, Power Supplies, Cables & Connectors.